
Attention

HP 9114 Owners



Battery Life

This product contains rechargeable batteries.

Over time, these batteries will lose their charge. Please recharge them before initial use of the 9114. Failure to keep the battery fully charged reduces operating times.

Please refer to the manual for charging instructions.

WARNING

Modification Hazard

DO NOT ATTEMP to modify the 9114 power supply or battery pack. Modifications may create a shock or energy hazard.

HP Computer Museum
www.hpmuseum.net

For research and education purposes only.

USING YOUR DISC DRIVE

Supplement to manual P/N 09114-90005 Dated October 1985

Introduction

This supplement contains operating information on the following computers:

HP Portable and HP Portable Plus
HP Series 70
HP Series 40
IBM PC and PC XT

HP Portable and HP Portable Plus Operations

System Configuration

External disc drives are labeled starting with drive C. As many as eight single disc drives can be connected (drives C, D, E, F, G, H, I, and J). Turn on all the equipment. The first step is system configuration.

1. When the P.A.M. menu appears on the screen, press the following softkey:

*SYSTEM
CONFIG*

This is softkey f6.

2. The display that appears is shown next. There are three lines that have to do with external disc drives. These lines are the only lines of interest at this time. These lines are "Memory/Edisc:", "External disc drives:", and "Disc write verify:." Please locate these; they are the first three lines.

[System Configuration

]

*Memory / Edisc: 160K / 112K
External disc drives: 1
Disc write verify: Off
Power Save mode: On
Display timeout: 5 min
Cursor: Underscore
Console Mode: HP
Console Font: HP*

*Beep: Long
Plotter Interface: HP-IL
Printer: HP Graphics / Alpha
Printer Interface: HP-IL
Print pitch: Normal
Print line spacing: 6 lines/inch
Printer skip perf: Yes*

The default configuration for "Memory/Edisc:" should be used at this time. This line must be changed only if you run out of room in the memory or electronic disc. A warning is displayed if this ever happens to you. Space can be taken from either memory or electronic disc and allocated to the other when needed.

The next line of importance is "External disc drives:". The default configuration for an external disc drive is NONE. This must be changed to "1" or the number of HP 9114Bs you have connected to your system. Press the cursor control keys (arrow keys – top

right) until the "External disc drives:" line is highlighted. Then press the next and previous softkeys until you obtain the proper number.

The other line of interest is "Disc write verify:". This function can be off or on. When on, everything written to the disc is verified or checked to ensure that it is correct. This takes about twice as long, but ensures correct data on the disc. When off, the data is just written to the disc. Nothing needs to be done at this time, but you should know that verify is available. When the system configuration display is correct, press the Exit Config softkey.

The HP Portable and Portable Plus automatically assign each disc drive they see on the HP-IL (loop). Tracing from the "OUT" HP-IL cable, the first disc drive is assigned the letter C, the next disc drive is assigned D, and so on until the maximum of 8 external drives have been assigned. You need to know these letter assignments as they are used whenever you specify commands that store or retrieve data from the external disc.

Disc Formatting

The HP 9114B uses double-sided discs. Data is written on both sides of the disc. Thus the normal formatting procedure is double-sided formatting. Single-sided formatting is allowed for transferring data from older systems. See the next section for single-sided formatting.

Before a flexible disc can be used for the first time, it must be formatted. Formatting establishes the directory and volume label as well as verifying that the media is not damaged. Shown next are two ways to format discs. Insert a blank disc into the disc drive.

1. From the P.A.M. display, pressing the File Manager (f2) softkey gets you to a Format softkey. Press the key labeled Format (f5) and answer the next questions.

"Enter the disc to format." The first disc drive is assigned the letter C. Type **C:** and press Return.

"Enter a volume label (optional)." The volume label is the name you want to call the disc. This can be up to 11 characters. For example, let's call this disc "First." Type **FIRST** and press Return.

The information is displayed on the first two lines below the cursor. Press the Start Format key (f1) if these two lines are correct.

"Formatting Disc. Please wait." appears on the display. Formatting a disc takes about 1 1/2 minutes. The interleave used with this formatting method is 8, the optimal interleave for HP Portables/9114B operation.

After formatting is complete, pressing the Exit Format (f8) softkey returns you to the main File Manager display. To exit File Manager, press the Exit File Manager softkey. This ends the format procedure.

2. The second method of formatting discs is to use the MS-DOS Format command. From the initial P.A.M. display, tabbing over to the area called "DOS Commands" and pressing Return allows you to use the DOS command called **FORMAT**. The interleave used in this command is 8, the optimal interleave for your HP Portables/9114B system.

Type **FORMAT C:** and press Return.

"Press any key to begin formatting C:" is displayed. Press any key on the keyboard. Formatting takes about 1 1/2 minutes.

After formatting is complete, there is another prompt on the display, "Volume label (11 characters, Enter for none)?". Press Return if you don't want a label or Enter the name and press Return if you want to label the volume.

When completed, "Format another (Y/N)?" appears on the display. Typing **N** gets you back to entering MS-DOS commands. Type **EXIT** to return to P.A.M.

Formatting Single-sided

The HP Portables/9114B system can format double-sided discs in a single-sided format. This is allowed for data compatibility with other 3 1/2-inch disc systems. There is a utility called "Format.Com" on the utility disc supplied with your HP Portable or Portable Plus computer. You must load the "Format.Com" utility into your HP Portables. Use the following sequence.

Place the Utility disc into your HP 9114B.

Tab over to the DOS Command block and press Start Applic.

From the MS-DOS command display, type:

COPY C: FORMAT.COM A: and press Return

This loads the utility and allows you to use the extra parameters explained in the following **FORMAT** command.

The MS-DOS command that allows this compatibility with its parameters is shown next.

Format C:/W -Single-sided
/X -Double-sided with 256 byte sectors
/Y -Double-sided with 512 byte sectors
/Z -Double-sided with 1024 byte sectors



Copying to and from the Electronic Disc

Two MS-DOS commands are used when transferring files (data and programs) between the electronic and external discs. These commands are **COPY**Check Disc (**CHKDSK**). The **DIR C:** command is used to list the file directory on the external disc.

Now, from the P.A.M. display, let's tab to MS-DOS Command section and press (Return or Start Applic). This puts the HP Portables into MS-DOS command mode. Type the next line(s) to display the file directory.

DIR C: and press Return for the external disc

or

DIR A: and press Return for the electronic disc

When using the **COPY** command, don't forget the space between the filename and the destination address (filename A: and filename C:); this also applies to the space between the * and destination address (* C: and * A:) when copying the entire disc.

COPY C:filename A:
and pressing Return – copies the file specified from the external disc C to the electronic disc A.

COPY A:filename C:
and pressing Return – copies the file specified from the electronic disc A to the external disc C.

COPY A:*.* C:
and pressing Return copies the entire electronic disc to the external disc.

COPY C:*.* A:
and pressing Return copies the entire external disc to the electronic disc.

The **CHKDSK** command is used to check the available disc space. This command can be used to ensure space is available before transferring files. If you get the "Insufficient Disc Space" error when transferring files, you can either allocate more space for the electronic disc (if this is the disc that is out of space) or insert another formatted disc into the external drive. To gain more space for the electronic disc, you can either purge some existing file or get the space from the memory space. Memory space is allocated using the first line in the display described earlier – see *System Configuration* in this section.

CHKDSK C:

and pressing Return – displays the usable space remaining on the external disc.

CHKDSK A:

and pressing Return – displays the usable space remaining on the electronic disc.

Typing **EXIT** gets you back to the P.A.M. display.

Error Messages

The following error messages can occur with HP Portables.

"Non – DOS Disc Error Reading Drive __." The disc contains a non recognizable volume label.

"No Disc in Drive – Drive Not Ready – Error Reading Drive __."

These three errors indicate the disc drive does not contain a disc, or the disc drive is not turned on or connected (HP-IL cable), or the disc drive contains a bad disc or a disc formatted by another type of computer. In the case of the bad disc, the problem could be a bad file; try this several times and access different files to determine the extent of disc damage.

"Disc Space Unavailable" – The electronic disc or external disc is full.

Series 70 Operation

Operation with the HP 71B

Disc storage for the HP 71B is handled using the following commands: **ASSIGN IO**, **INITIALIZE**, **COPY**, and **CAT**.

ASSIGN IO is used to assign an address to each device on the loop. A position as well as a two letter code is used to establish this address.

ASSIGN IO “:DD”

and pressing END LINE – assigns DD to the first or next sequential HP-IL device on the loop. Also assigned is the position or device number. This is the number (1, 2, 3, etc.) of the device on the HP-IL cable. Numbering is obtained sequentially by position on the HP-IL cable as you trace the “OUT” cable from your computer. The DD is used as an example here. Whatever two characters you use can be used in the **INITIALIZE**, **COPY**, and **CAT** commands. After you execute the **ASSIGN IO** statement, you can address a device by the position number or the two letter code. This will be used later in some examples.

INITIALIZE is used to get the disc ready to receive data and to establish a volume label, as well as to verify that the media is not damaged.

INITIALIZE “TEST:DD”

and pressing END LINE – establishes the volume label of TEST on the disc at device location DD. You might want to write the volume name you give the disc on the disc jacket label. This volume name can be used to access the disc using the **CAT** and **COPY** commands and is very easy to forget. Initializing takes approximately 1 1/2 minutes. The disc access light on the disc drive goes out when initializing is complete.

COPY allows you to move files and data to and from the disc drive. The next two examples of the **COPY** command are shown three times. Each time a different form of HP-IL addressing is used.

Example **one** – Copying a file from the HP 71 to the disc drive.

COPY filename TO :1

COPY filename TO.TEST

COPY filename TO :DD

and pressing END LINE – writes the file specified to the disc.

Example **two** – Copying a file from the disc drive to the HP 71.

COPY filename:1

COPY filename.TEST

COPY filename:DD

and pressing END LINE – reads the file specified from the disc.

CATALOG (CAT) is used to obtain a list of the files that are stored on the disc. The display scrolling keys are used to view the different files (scrolling up and down) and the entire file name and data concerning each file (scrolling to the end of the display).

CAT :1

and pressing END LINE – displays the filenames on the disc.

The “1” represents the position of the disc drive on the HP-IL.

CAT.TEST

and pressing END LINE – displays the filenames on the disc.

TEST is the volume name.

CAT :DD

and pressing END LINE – displays the filenames on the disc.

DD was the assignment made in the previous **ASSIGN IO** command.

Formatting Singled-sided Discs

The HP 9114B Disc Drive is a double-sided disc drive. When you initialize a disc, the disc is initialized in double-sided format. For single-sided compatibility and data exchange with other computers, the following program allows your HP 71B/9114B system to initialize a double-sided disc in single-sided format.

After keying in and starting the program, you are prompted for the address of the disc drive. The address is the position of the HP 9114B in the HP-IL (loop). The program also asks for the number of directory entries and a volume label. The directory entries are usually set to 200. The volume label is a name you give the disc. This name can be six characters or less. See the HP 71 Owner's manual for more details. As a final question, the program asks if you want to initialize another disc. Y for yes and N for no is the required response. After this, the program either repeats or stops.

```
0010 ! SINGLE SIDED FORMAT UTILITY FOR 71B AND THE HP 9114B
0020 INPUT "ADDRESS OF DRIVE? ";A
0030 RESET HPIL
0040 CLEAR :A
0050 SEND UNL MTA LISTEN A SAD 5 DATA CHR$(49)&CHR$(243) END 95
0060 SEND UNL MTA LISTEN A SAD 14
0070 SEND END 4
0080 SEND UNL MLA TALK A SAD 16
0090 ENTER :LOOP USING "#,b";Q
0100 IF Q = 0 THEN GOTO 'NOERR'
0110 DISP "ERROR"
0120 STOP
0130 'NOERR': !
0140 INPUT "NUMBER OF DIRECTORY ENTRIES? ";N
0150 INPUT "VOLUME LABEL? ";V$
0160 INPUT "PRESS END LINE TO START";C$
0170 DISP "INITIALIZING"
0180 INITIALIZE V$&"":&STR$(A),N
0190 INPUT "FORMAT ANOTHER(Y/N)? ";C$
0200 IF C = $"Y" THEN GOTO 140
0210 CLEAR :A
0220 STOP
```

Operation with the HP 75

Disc storage for the HP 75 is handled using the following commands: **ASSIGN IO**, **INITIALIZE**, **COPY**, and **CAT**.

ASSIGN IO is used to assign a device code to each device on the loop. A device code is generally a two character code representing each device. In our example, we use DD to represent Disc Drive.

ASSIGN IO 'DD'

and pressing Return -- assigns DD to the first or next sequential HP-IL device on the loop. The DD is used as an example here. Whatever two characters you use must be used in the **INITIALIZE**, **COPY**, and **CAT** commands. This is used in the examples.

INITIALIZE is used to get the disc ready to receive data.

INITIALIZE ':DD'

and pressing Return – prepares the disc at device code DD to receive data. The device code must be used in all the commands to this device. Initializing takes approximately 1 1/2 minutes. The disc access light on the disc drive goes out when initializing is complete.

COPY allows you to move files and data to and from the disc drive.

COPY 'filename' TO 'filename:DD'

and pressing Return – writes the file specified to the disc.

COPY 'filename:DD' TO 'filename'

and pressing Return – reads the file specified from the disc.

CATALOG (CAT) is used to obtain a list of the files that are stored on the disc. The display scrolling keys are used to view the different files (scrolling up and down) and the entire file name and data concerning each file (scrolling to the end of the display).

CAT ':DD'

and pressing END LINE – displays the filenames on the disc.

Formatting Single-sided Discs

The following utility can be entered into the HP 75 to format 3 1/2-inch double-sided discs in single-sided format. These discs are compatible with other HP disc products that use single-sided drives. This utility requires either the I/O Utilities (00075-13013) or the I/O ROM (00075-15001) to be resident in your HP 75.

This utility prompts you for the device code. This is the device code specified using the **ASSIGN IO** command. The utility then prompts you for the number of directory entries. A typical number of directory entries for the single-sided formatted disc is 200. After RTN is pressed, the HP 75 begins the format operation.

```
10 ! SINGLE SIDED FORMAT UTILITY FOR HP 75 AND HP 9114B
20 ! THIS PROGRAM REQUIRES EITHER I/O UTILITIES OR THE I/O ROM
30 INPUT "DEVICE CODE OF DRIVE? ";A$
40 SENDIO A$,"UNL,LAD#,SDC',"
50 SENDIO A$,"UNL,LAD#,CD:65,DS:31,DS:F3,EN:5F',"
60 SENDIO A$,"UNL,LAD#,CD:6E,EN:04',"
70 Q = $ENTIO$(A$,"TAD# ,CD:70,SDA')
80 IF Q = $CHR$(0) THEN 110
90 DISP "ERROR IN SETTING FORMAT"
```

```
100 GOTO 160
110 INPUT 'NUMBER OF DIRECTORY ENTRIES? ';N
120 INPUT "PRESS 'RTN' TO START";N$
130 INITIALIZE A$,N
140 INPUT "FORMAT ANOTHER (Y/N)? ";C$
150 IF C = $"Y" THEN 110
160 SENDIO A$,'UNL,LAD# ,SDC',"
170 END
```



Series 40 Operations

Disc storage for the Series 40 is handled using the following commands: **NEWM**, **DIR**, **WRTP**, **READP**, **WRTA**, and **READA**. These commands are explained next. For a more complete explanation of these commands see the HP-IL Module Owner's Manual (P/N 82160-90001).

NEWM

The **NEWM** command is used to initialize the flexible disc. **NEWM** is automatically directed to the first device on the loop. The first device must be your HP 9114B. Pressing the following keys initiates the **NEWM** command.

XEQ ALPHA NEWM ALPHA

The calculator then prompts you for the number of directory entries or number of files you plan to store on the the disc. This number can be as high as 447, but generally is around 80. The more directory entries, the longer the search times when using the **DIR** (directory) command.

When you see **NEWM**, type **080** or the number of directory entries you want. One to two seconds after you type the final number, the disc access light should come on as the 9114B begins the 1 1/2 minute initialize sequence.

DIR

The **DIR** command is used to read the directory which includes the file names, file types, and file sizes. **DIR** always accesses the first device on the loop which must be the tape drive. Press the following key sequence.

XEQ ALPHA DIR ALPHA

DIR uses the ALPHA register to display directory information.

WRTP, READP, WRTA, and READA

These four operations require that you place the program name into the ALPHA register before you execute the operation. To execute the operations, press the following keys.

XEQ ALPHA READP ALPHA

Substitute your operation in place of the READP.

WRTP – Write program

READP – Read program

WRTA – Write all (the entire calculator contents and memory modules are written to the mass storage).

READA – Read all (the entire calculator contents and memory modules are read from the mass storage).

ASCII Data Files

The two ASCII data file commands **SAVEAS** and **GETAS** were not designed to operate with a disc drive that powers down when not in use. An error is generated when you use these commands because the disc drive does not power up fast enough. When programming with these two commands, set up the following sequence.

Disable the errors

Send command (**SAVEAS** or **GETAS**) – This starts the disc drive.

Enable the errors

Resend the command (**SAVEAS** or **GETAS**) – Executes the command.

SAVEAS and **GETAS** are explained in the section titled “Accessing Mass Storage Files” in the Series 40 Owner’s Manual P/N 00041-90492.

Series 40/9114 Utility

The Series 40 calculators can access 130 kbytes of the HP 9114B’s 630 kbytes. The following utility, when entered into a Series 40, allows you to access the full 630 kbytes. The utility requires that the 82183A Extended I/O Module be installed in your calculator. Additionally, this utility is available from the User’s Library (#41-09114) on 3 1/2-inch media.

There are six operations or functions that are affected by this utility when they are executed: WRTP, WRTPV, WRTS, WRTK, WRTA, AND CREATE. These functions must create new directory entries. All these functions operate the same as before (documented in the HP-IL Module Owner's manual). These functions require correct information be placed in the ALPHA and (in some cases) the X registers.

Following are the 4 most common errors you can get when using this utility.

Error Number	Error Description
18	Uninitialized Media
20	No Media
21	Low Battery
99	Other Errors (This includes the write-protect disc error.)

The Utility is listed next.

```

01*LBL "DSC?"
02  ADRON          --
03  16
04  FINDAID       -- FIND MASS STORAGE DEVICE
05  X#0?         --
06  GTO "VLL"
07  "NO DRIVE"
08  PROMPT
09  GTO "DONE"
10*LBL "VLL"
11  SELECT
12  0
13  ENTER
14  XEQ "SEEK"    -- SEEK TO VOLUME LABEL TRACK 0, RECORD 0
15  RCLSEL
16  TAD
17  2
18  DDT          -- READ RECORD
19  XEQ "WAIT"
20  4
21  DDT          -- SWAP BUFFERS
22  XEQ "WAIT"
23  1
24  DDT          -- SEND BUFFER 1
25  8
26  INAN
27  1
28  ATOXX
29  128
30  X#Y?         -- CHECK FOR NON-LIF DISC
31  GTO "NL"

```


32	XEQ "B2D"	- READ LOCATION OF 1ST RECORD OF DIRECTORY
33	STO 01	
34	4	
35	INAN	
36	XEQ "B2D"	- DIRECTORY LENGTH
37	1	--
38	-	
39	RCL 01	
40	+	- CONSTRUCT COUNTER TO SEARCH DIRECTORY
41	STO 02	
42	1 E3	
43	/	
44	ST+ 01	--
45	RCL 01	
46	INT	
47	XEQ "D2B"	
48	XEQ "SEEK"	- SEEK TO START OF DIRECTORY
49	*LBL 10	
50	RCLSEL	
51	TAD	
52	2	- READ RECORD FROM DIRECTORY
53	DDT	
54	XEQ "WAIT"	
55	RCLSEL	
56	LAD	
57	9	
58	DDL	- COPY BUFFER 0 TO BUFFER 1
59	XEQ "WAIT"	
60	3	
61	DEVL	
62	234	- SET BYTE POINTER TO LAST ENTRY IN RECORD
63	OUTXB	
64	RCLSEL	
65	TAD	
66	1	
67	DDT	- SEND BUFFER 1
68	INXB	
69	INXB	
70	+	
71	510	- FOUND A RECORD WITH ROOM
72	X=Y?	
73	GTO "RS"	
74	XEQ "B2D"	--
75	STO 03	- SAVE LOCATION AND LENGTH OF FILE IN LAST ENTRY IN RECORD
76	XEQ "B2D"	
77	ST+ 03	
78	ISG 01	
79	GTO 10	--
80	*LBL "DF"	- DIRECTORY FULL-PACK OR USE NEW MEDIA
81	"DIR FULL"	
82	PROMPT	
83	GTO "DONE"	
84	*LBL "NL"	- EXIT IF NOT A LIF DISC
85	"NOT LIF DISC"	
86	PROMPT	
87	GTO "DONE"	
88	*LBL "RS"	- START SEARCH OF RECORD FOR LOCATION TO WRITE DUMMY ENTRY
89	RCLSEL	
90	LAD	

91	3	
92	DEVL	
93	CLX	
94	OUTXB	- RESET BYTE POINTER TO 0
95	RDN	
96	TAD	
97	1	
98	DDT	- SEND BUFFER 1
99	1.007	
100	STO 04	
101	*LBL 12	
102	12	
103	INAN	
104	ATOXR	
105	ATOXR	- READ 2 BYTES OF FILETYPE - IF BOTH 255,
106	+	THEN THIS IS WHERE WE WRITE DUMMY ENTRY
107	510	
108	X=Y?	
109	GTO "WRT"	
110	XEQ "B2D"	--
111	STO 03	
112	XEQ "B2D"	- SAVE LOCATION AND LENGTH OF FILE-
113	ST + 03	NEEDED FOR DUMMY ENTRY
114	12	
115	INAN	
116	ISG 04	
117	GTO 12	
118	RCL 01	
119	INT	
120	RCL 02	
121	X=Y?	- IF LAST RECORD - LAST ENTRY OF RECORD, DI-
122	GTO "DF"	RECTORY IS FULL - LAST ENTRY RESERVED BY 41
123	*LBL "WRT"	
124	RCL 01	
125	INT	
126	XEQ "D2B"	
127	XEQ "SEEK"	- SEEK TO TRACK AND RECORD WHERE DUMMY
128	RCLSEL	ENTRY IS TO BE WRITTEN
129	LAD	
130	3	--
131	DDL	
132	RCL 04	
133	1	
134	-	- SET BYTE POINTER
135	32	
136	*	
137	OUTXB	--
138	RCLSEL	
139	LAD	
140	6	- PARTIAL WRITE MODE
141	DDL	
142	"D (10 spaces)"	- DUMMY DIRECTORY ENTRY
143	0	
144	XTOAR	
145	XTOAR	
146	XTOAR	
147	XTOAR	
148	RCL 03	
149	XEQ "D2B"	



150	XTOAR	
151	RDN	
152	XTOAR	
153	0	
154	XTOAR	
155	XTOAR	
156	RCL 05	
157	FC? 09	
158	GTO 00	
159	32	
160	/	
161	ENTER	
162	INT	
163	X# Y?	
164	ISG X	
165	FIX 4	
166	*LBL 00	
167	XEQ "D2B"	-- LENGTH OF FILE
168	XTOAR	
169	RDN	
170	XTOAR	
171	20	
172	OUTAN	-- WRITE TO TAPE
173	ADRON	
174	RCLSEL	
175	LAD	
176	8	-- CLOSE RECORD
177	DDL	
178	SF 10	
179	CLA	
180	ARCL 06	--
181	ARCL 07	
182	ARCL 08	-- RECALL CONTENTS OF ALPHA + X BEFORE
183	ARCL 09	41 FUNCTION WAS ATTEMPTED
184	RCL 05	--
185	GTO IND 00	
186	*LBL "WRTP"	--
187	CF 10	
188	CF 09	
189	1	-- WRITE PROGRAM
190	STO 00	
191	9	
192	STO 05	
193	*LBL 01	
194	SF 25	
195	WRTP	
196	GTO "OP"	--
197	*LBL "WRTPV"	--
198	CF 10	
199	CF 09	
200	2	
201	STO 00	
202	9	-- WRITE PRIVATE PROGRAM
203	STO 05	
204	*LBL 02	
205	SF 25	
206	WRTPV	
207	GTO "OP"	--
208	*LBL "WRTS"	--

```

209 CF 10
210 SF 09
211 3
212 STO 00
213 1          - WRITE STATUS
214 STO 05
215*LBL 03
216 SF 25
217 WRTS
218 GTO "OP"   --
219*LBL "WRTK" --
220 CF 10
221 CF 09
222 4
223 STO 00
224 1          - WRITE KEYS
225 STO 05
226*LBL 04
227 SF 25
228 WRTK
229 GTO "OP"   --
230*LBL "WRTA" --
231 CF 10
232 CF 09
233 5
234 STO 00    - WRITE ALL
235 11
236 STO 05
237*LBL 05
238 SF 25
239 WRTA
240 GTO "OP"   --
241*LBL "CREATE" --
242 CF 10
243 SF 09
244*LBL 06
245 SF 25    - CREATE
246 CREATE
247 STO 05
248 6
249 STO 00
250 GTO "OP"   --
251*LBL "B2D"  --
252 4
253 INAN
254 ATOXR     - TAKE 4 BYTES FROM LOOP AND RETURN TO X DE-
255 ATOXR     CIMAL # OF LAST 2 BYTES, (16-BIT WORD)
256 256
257 *
258 +
259 RTN      --
260*LBL "D2B" --
261 ENTER
262 ENTER
263 256
264 MOD      - BREAK DECIMAL # IN X INTRO 2 BYTES
265 X<>Y     XY MOST SIG. BYTE
266 LASTX    Y  LEAST SIG. BYTE
267 /

```

268	INT	
269	RTN	--
270*	LBL "OP"	- EXECUTED AFTER FUNCTION ATTEMPT
271	FS? 25	
272	GTO "WP?"	- IF SUCCESSFUL, GOTO WP?
273	99	IF NOT, WAS IT 2ND TRY?
274	FS? 10	IF 2ND TRY, EXIT
275	GTO "ERROR"	IF 1ST TRY, SAVE ACYNA AND X + TRY AGAIN
276	6.009	
277	STO L	
278*	LBL 07	
279	ASTO IND L	
280	ASHF	
281	ISG L	
282	GTO 07	
283	GTO "DSC?"	
284*	LBL "WAIT"	- CHECK STATUS OF DRIVE
285*	LBL 11	
286	SF 25	- KEEP CHECK IF BUSY
287	INSTAT	
288	FC?C 25	- RETURN IF IDLE
289	GTO 11	
290	FS? 05	- DISPLAY ERROR # IF ERROR
291	GTO 11	
292	FS? 04	
293	GTO "ERROR"	
294	RTN	
295*	LBL "WP?"	- IF SUCCESSFUL ON 1ST TRY, EXIT
296	FC? 10	
297	GTO "DONE"	
298	2	--
299	RCL 00	- IF NOT WRTP OR WRTPV, ENT
300	X>Y?	
301	GTO "DONE"	--
302	RCL 01	
303	INT	
304	XEQ "D2B"	- MUST ALTER DIR ENTRY FOR WRTP AND WRTPB
305	XEQ "SEEK"	TO SHOW CORRECT # OF REGISTERS CONSUMED -
306	RCLSEL	NO WAY TO DETECT THIS WHEN DUMMY
307	LAD	ENTRY IS WRITTEN
308	3	
309	DDL	
310	RCL 04	
311	32	
312	*	
313	4	
314	-	
315	OUTXB	
316	RCLSEL	
317	TAD	
318	1	
319	DDT	
320	INXB	
321	INXB	- READ LENGTH OF FILE IN BYTES
322	X>0?	
323	ISG Y	
324	FIX 4	
325	RDN	
326	STO 05	

```

327 RCLSEL
328 LAD
329 3
330 DDL --
331 RCL 04
332 32
333 * -- SET BYTE POINTER
334 13
335 -
336 OUTXB --
337 RCLSEL
338 LAD
339 6 -- PARTIAL WRITE MODE
340 DDL
341 RCL 05 -- WRITE CORRECT # OF RECORDS
342 OUTXB
343 RCLSEL
344 LAD
345 8
346 DDL -- CLOSE RECORD
347 GTO "DONE"
348*LBL "SEEK" -- SEEK TO TRACK AND RECORD SPECIFIED BY
349 ADROFF CONTENTS OF X AND Y REGISTERS
350 RCLSEL
351 LAD
352 4
353 DDL
354 RDN
355 RDN
356 OUTXB
357 RDN
358 OUTXB
359 XEQ "WAIT"
360 ADRON
361 RTN
362*LBL "ERROR" -- DISPLAY ERROR #
363 CF 10
364 "ERROR: "
365 ARCL X
366 AVIEW
367 STOP
368*LBL "DONE" -- EXIT
369 CF 10
370 END

```

Using the 9114B with the IBM PC (PC-XT)

Introduction

This section shows you the following two procedures:

- Step 1 – How to install the HP-IL routines on the IBM PC so you can use the 3 1/2-inch disc drive with your computer.
- Step 2 – How to use your 3 1/2-inch disc with your IBM PC.

Before going any further, be sure the HP 82973A HP-IL Interface Card is installed per the HP 82973A manual. The 5 1/4-inch disc that comes with the interface card will be used in the following procedure. This disc is called the HP 82973A HP-IL Interface Disc.

Step 1 – Installing the HP-IL Driver on the IBM PC

This section shows you how to transfer two of the files from the HP 82973A HP-IL Interface Disc to your master DOS disc (the disc you use to boot your system). If you have an IBM PC, this master boot disc will be a 5 1/4-inch flexible disc. If you have the IBM PC-XT, this master boot disc would commonly be the Winchester disc at drive C.

First, for you IBM PC users, let's make a copy of your master boot disc. Begin at step 1 of this section. For you IBM PC-XT users, start with step 2 of this section.

1. Use the **DISKCOPY** command and make a copy of your DOS boot disc. First, boot up your system by placing the boot disc in drive A. Turn the system on and Enter the date and time. Type the next line.

DISKCOPY A: B:

Press Enter, and follow the diskcopy instructions.

Use the new copy of your master DOS disc to make all the following changes. This copy is now in drive B. Remove your master boot disc and put it away for now. Place the copy you have just made in drive A. Continue to step 2.

2. Check to see if you have a file called CONFIG.SYS on your DOS disc by typing the next line and pressing Enter.

DIR CONFIG.SYS

If the file is found, the next two lines will appear on your display.

Config Sys

1 File(s)

If CONFIG.SYS is on your DOS disc, perform only **Procedure A** below.

If CONFIG.SYS is NOT on your DOS disc, perform only **Procedure B** below.



PROCEDURE A:

Type in the next line and press Enter.

TYPE CONFIG.SYS

The contents of the CONFIG.SYS file is now displayed. You probably should write these files down as you will have to retype them.

Type the next two lines and add the files you just wrote down beginning at the place indicated. When all the files are added, the Z character is added by holding down the **Ctrl** key as you press the Z key.

COPY CON CONFIG.SYS

DEVICE = HPIL.SYS

Add the files you wrote down above

Z (Ctrl Z)

Now press the Enter key to store the file to your DOS disc.

PROCEDURE B:

Type the next two lines. The Z character is added by holding down the **Ctrl** key as you press the Z key.

COPY CON CONFIG.SYS

DEVICE = HPIL.SYS

Z (Ctrl Z)

NOTE

If you set the address on the interface card to an address other than 1700 when you installed the HP-IL interface, you must specify your address when you type **DEVICE=HPIL.SYS**. For example, if you set the address of the interface card to 2200, enter the following line in CONFIG.SYS:

DEVICE = HPIL.SYS /A 2200

3. Copy the files **HPIL.SYS** and **HPILFOR.COM** from the HP 82973A HPIL Interface software disc to the DOS disc.

EXAMPLE: With the DOS disc in drive A (IBM PC), insert the HP-IL interface disc into drive B and type the next commands. If you have the IBM PC-XT insert the HP 82973A disc into the flexible disc drive and type the next two commands. This drive (IBM PC-XT) responds to both A: and B: identifiers.

After typing each line, press Enter and wait for the file to copy.

```
COPY B:HPIL.SYS  
COPY B:HPILFOR.COM
```

4. At this time, connect the HP 9114B to the HP-IL card and turn the disc drive on. Also remove the HP 82973A HPIL Interface disc. This should be done before you reset the computer.

With the DOS disc in drive A, reset the IBM PC so that the operating system is re-booted. Reset the IBM PC-XT so its operating system re-boots from the Winchester. Reset on both computers is done by pressing the Alt, Ctrl, and Del keys at the same time.

HPIL.SYS is now installed if the display screen shows HP-IL being present.

NOTE

If you want to run HPLINK, you need to first remove HPIL.SYS from the system. This allows the IBM PC to reside on the HP-IL without being the system controller.

The easiest way to do this on the IBM PC is to boot your computer with the old DOS disc that does not contain the files CONFIG.SYS, HPIL.SYS, or HPILFOR.COM.

On the PC-XT, remove the following line

```
DEVICE = HPIL.SYS
```

from the file CONFIG.SYS and reboot the computer.

Step 2 – Using Your 3 1/2-inch Disc Drive with your IBM PC

The first step in using the 3 1/2-inch disc drive is to format the 3 1/2-inch discs. Formatting 3 1/2-inch discs must always be done using the HPILFOR routine that we installed on the operating system. The commands **DISKCOPY** and **DISKCOMP** will not work with the HP 9114B.

Data storage devices on the loop are assigned disc drive identifiers in a sequence following those already assigned on the IBM. For example, if you have disc drives A:, B:, and C: assigned to the IBM PC-XT and you have two HP-IL data storage units connected, the HP-IL units will be assigned the identifiers D: and E:. You can then use them as you would any of the disc drives on your IBM PC-XT.

The command to format a disc in the HP 9114B is shown next.

HPILFOR m:

The **m:** is the disc drive identifier of the disc you want to format.

For example, to format a disc using drive D:, type: .

HPILFOR D:

Before the computer formats the specified disc drive, it prompts you to press a key to start formatting. This ensures that you do not accidentally format a disc that you do not want erased. (**Remember that formatting a disc erases all information on that disc.**) After pressing the key to confirm that you want a disc formatted, the computer begins the formatting operation.

Once the disc is formatted, you can write data on it. The **Copy** command is shown next. When using the **Copy** command, don't forget the space between the filename and the destination address (filename A: and filename C:); this also applies to the space between the * and destination address (* C: and * A:) when copying the entire disc.

COPY C:filename A:

and pressing Enter – copies the file specified from disc C to disc A.

COPY A:filename C:

and pressing Enter – copies the file specified from disc A to disc C.

COPY A:*. * C:

and pressing Enter – copies the entire disc in drive A to the disc in drive C.

COPY C:*. * A:

and pressing Enter – copies the entire disc in drive C to the disc in drive A.

NOTE

To initialize an HP-IL disc in single-sided format on the IBM PC, use the /w parameter as shown next.

HPILFOR m:/w

Remember that the m parameter is the identifier of the disc drive containing the disc you want to format.

When using a HP Portable (or HP Portable Plus) on the loop when the IBM PC is a controller, the HP Portable must be running a program that enables it to be a device on the loop. Otherwise the IBM PC and the HP Portable will both attempt to be the loop controller. The result is that the loop will not operate until either the IBM PC or the HP Portable is disconnected from the loop.

Moving Data

You can use any formatting commands to move data between the HP Portable, the HP Portable Plus, the HP 150 Series, the HP Vectra PC, and the IBM PC.

There are two exceptions:

- To move data to one of the HP 150 Series, the disc must be formatted in the single-sided format if you are using an HP 9121 D/S or an HP 9133A/B/V/XV.
- Use discs formatted with the /Z option with the HP Portable or HP Portable Plus.